

# Coin100 / Coin120

Coin counting & bagging machines

**procoin**  
cash handling for professionals



- ➔ Counts and batches single denomination coins
- ➔ Rejects any wrong denomination coin\*
- ➔ Large Hopper extension included

## Procoin GmbH

Silostr. 31/33a  
65929 Frankfurt am Main  
Tel. +49 69.2440 424-0  
Fax +49 69.2440 424-24

We make cash flow.



info@procoin.eu  
www.procoin.eu

Images may differ from the delivered product and partly show special equipment.

# Coin100 / Coin120

## Coin counting & bagging machines

The Coin100 / Coin120 is an entry level single denomination coin counting/bagging solution. It is mainly used for counting coins or tokens. It can continuously count and count to a preset number. It counts pre-sorted coins. The double dial adjustment allows simple setup. One setting of the dial is enough to select the proper denomination.

\*Coins which are smaller by at least 0.5 mm than the present set denomination are off sorted automatically. Count totals can be stored in memory.

With the Coin100 / Coin 120 counting machine, businesses can quickly and accurately count and sort large quantities of loose coins. For single denomination currency this coin counting machine is the most accurate and fastest method to count and sort coins.

**The Coin120** comes with an even greater and motorized hopper capacity. To make service easier the whole hopper can be lifted without dismounting parts.



### Counting speed

Max. 2.500 Coins/Min

### Hopper capacity

Max. 4.000 coins  
(without the hopper extender installed for coins diameter of 15 mm and thickness of 1.1 mm.)

Max. 12.000 coins  
(with the hopper extender installed for coins diameter of 15 mm and thickness of 1.1 mm.)

Max. 18.000 coins **Coin120**

### Countable coin size

Thickness: 0.7 to 3.9 mm  
Diameter: 14 to 34 mm

### Max. counting display

9999999

### Counting mode

Continuous Counting Mode  
Batch Counting Mode  
Accumulation Counting Mode



Optional: **coin tube set**

Optional:  
**external customer display**

Optional:  
**computer interface**

### Power Requirements

AC 120V  $\pm$  10%, 60Hz  
or AC 220V  $\pm$  10%, 50Hz

### Power consumption

70 W (During operation)  
**Coin100**  
85 W (During operation)  
**Coin120**

### Dimension

270 (w) x 362 (d) x 240 (h) mm  
**Coin100**  
296 (w) x 373 (d) x 390 (h) mm  
**Coin120**

### Net weight

11 Kg **Coin100**  
14 Kg **Coin120**

### More reliable devices from Procoin:

Coin Counter and Sorter | Coin Packaging Machines |  
Banknote Counter and Sorter | Self-Service Machines

**Please contact us and ask!**

### Procoin GmbH

Silostr. 31/33a  
D 65929 Frankfurt am Main  
Tel. +49 69.2440 424-0  
Fax +49 69.2440 424-24

# We make cash flow.



info@procoin.eu  
www.procoin.eu